VALVES

Current Equipment Type

TYPE **CI7SM** B12A (DUODECAL) BASE



The Brimar C17SM is a rectangular 90° deflection angle teletube with electrostatic focus, an aluminised screen and external conductive coating. The screen colour is white with a grey glass faceplate with a transmission of approximately 70 per cent.

RATINGS

Heater Voltage							6.3 volts
Heater Current							0.3 amp.
Final Anode Volt	age ((a2 + 4)					18 kilovolts abs. max.
Final Anode Volt	age ($\sqrt{22 + 4}$					12 kilovolts min.
Focus Anode Vol	tage	(Va3)					-500 to 1,000 volts max.
First Anode Volt	age ((a1)	•••		•••		500 volts max.
First Anode Volt	age ((a1)					250 volts min.
Grid Voltage (V,) Peal	<					2 volts max.
Heater to Cathoo	de Vo	Itage (V	hk) Ca	thode I	Positiv	e	200 volts max.
Heater to Cathoo	de Vo	Itage (V	hk) Ca	thode I	Positiv	e *	410 volts max.
Heater to Cathoo	de Vo	Itage (V	hk) Ca	thode I	Negati	ve	180 volts max.
Diagonal Deflecti	on A	ngle				·	90° approx.
		-					

* During warm-up, for a period not exceeding 45 seconds.

OPERATING CHARACTERISTICS

Final Anode Voltage			•••	•••		16 kilovolts
Focus Anode Voltage			••••			300 volts
First Anode Voltage					•••	300 volts
Peak to Peak Modulati	ing Vol	tage fo	r Beam	Curre	nt of	
150 μΑ	·					30 volts
Grid Voltage to cut-or	ff Beam	Curre	nt			-33 to -77 volts
				1.2		

For characteristic curve refer to type C21SM.

INTER-ELECTRODE CAPACITANCES

Grid to all				 		9.0 pF max.
Cathode to all			•••	 		6.0 pF max.
Final Anode to	External	Coat	ing	 •••	•••	1,500 pF max.

NOTES:

BRIMAR

- A. No harmful X-ray radiation is produced by this tube when operated at final anode voltages below 16 kV. At voltages above 16 kV some shielding may be necessary to protect against prolonged exposure at close range.
- B. Shift magnets when used should be mounted in such a position that they do not interfere with the passage of the electron beam through the gun. This position is normally immediately behind the scanning coils.

VALVES

BRIMAR



