



# engineering data service

from JEDEC release #2568, Aug. 31, 1959

## **ADVANCE DATA**

## MECHANICAL DATA

Bulb_						T-12
Base <sup>1</sup>	B7-227,	Short	Medium	Shell	Octa	d, ?⊸Pin
Cap	_					CI-34
Outline						12-18
Basing <sup>l</sup>						3C
Cathode				Çoa	ated	Filament
Mounting	Position	n				Any

## ELECTRICAL DATA

#### FILAMENT CHARACTERISTICS

Filament Voltage 1.25 Volts
Filament Current 200 Ma
Maximum Heater Voltage Range<sup>2</sup> 1.05 - 1.45 Volts

## DIRECT INTERELECTRODE CAPACITANCE

Plate to Filament and Internal Shield 1.4 puf

RATINGS (Design Maximum System)<sup>2</sup>

## Flyback Voltage Rectifier3

Inverse Plate Voltage			
Total DC and Peak	28,000	Volts	Max.
DC	24,000	Volts	Max.
Peak Plate Current	50	Ma	Max.
Average Plate Current	0.5	Ma	Max.

## CHARACTERISTICS

Tube Drop for Tb = 7 Ma (approx.) 100 Volts


#### NOTES:


- 1. Socket terminals 1, 3, 4, 5, 6 and 8 may be connected to terminal 7 or to a corona shield which connects to terminal 7. Terminals 4 and 6 may be used as tie points at or near filament potential.
- 2. Design-Maximum Ratings are limiting values of operating and environmental conditions applicable to a bogey electron device of a specified type as defined by its published data, and should not be exceeded under the worst probable conditions.

The device manufacturer chooses these values to provide acceptable serviceability of the device, taking responsibility for the effects of changes in operating conditions due to variations in device characteristics.

## QUICK REFERENCE DATA

The Sylvania Type 1N2 is a filamentary half-wave diode intended for service as the high voltage rectifier in television receivers and other high voltage rectifier applied cations.





#### SYLVANIA ELECTRONIC TUBES

A Division of SYLVANIA ELECTRIC PRODUCTS, Inc.

RECEIVING TUBE
OPERATIONS
EMPORIUM, PENNSYLVANIA

Prepared and Released By The TECHNICAL PUBLICATIONS SECTION EMPORIUM, PENNSYLVANIA

> July 15, 1959 Page 1 of 2

#### SYLVANTA

**IN2** 

Page 2

## NOTES: (Continued)

- 2. The equipment manufacturer should design so that initially and throughout life no design-maximum value for the intended service is exceeded with a bogey device under the worst probable operating conditions with respect to supply-voltage variation, equipment component variation, equipment control adjustment, load variation, signal variation, and environmental conditions.
- 3. For operation in a 525 line, 30 frame system as described in "Standards of Good Engineering Practice for Television Broadcast Stations; Federal Communications Commission", the duty cycle of the voltage pulse must not exceed 15 per cent of one scanning cycle.

## WARNING:

X-ray radiation shielding may be necessary to protect against possible danger of personal injury from prolonged exposure at close range if this tube is operated at higher than the manufacturer's Maximum Rated Plate Voltage or 16,000 volts, whichever is less.