Duplexers and Duplexer Tubes from Microwave Associates



A B C D'S OF PASSIVE HARDBRAZED TR LIMITERS

A. PASSIVE

- 1. ELIMINATES IGNITOR WEAROUT
- 2. ELIMINATES IGNITOR SUPPLIES AND CIRCUITRY
- 3. ELIMINATES SHUTTERS IN SYSTEM
- 4. ELIMINATES SHUTTER SUPPLIES AND CIRCUITRY
- 5. ELIMINATES IGNITOR NOISE, IGNITOR INTERACTION, AND IGNITOR PHASE INSTABILITY
- 6. REMOVES IGNITOR CONSTRAINT ON GAS FILL

B. HARDBRAZED


- 1. TEMPERATURE INDEPENDENCE OF LEAKAGE AND RECOVERY TIME
- 2. CLEAN, CONTROLLABLE, MORE REPRODUCIBLE VEHICLE
- 3. LOWER INSERTION LOSS
- 4. IMPROVED VACUUM INTEGRITY
- 5. LONGER OPERATING LIFE
- 6. LONGER SHELF LIFE

C. TR

- 1. HIGH POWER HANDLING CAPABILITY WITH LOW LOSS
- 2. SUBSTANTIAL MOMENTARY OVERLOAD PROTECTION

D. LIMITER

- 1. LOWER LEAKAGE, POSITIVE RECEIVER PROTECTION
- 2. ALLOWS PASSIVE OPERATION OF TR TUBE



MICROWAVE ASSOCIATES

TYPICAL TR-TR LIMITER CAPABILITY

(Single Tube, Shunt Mount)¹

Capability				Frequency Ba	and		
		L	S	С	х	Ku	Ka
Frequency Range	GHz	1.2-1.4	2.7-3.6	4.9-5.9	8.4-10.5	15.5-17.5	32.5-35.0
Bandwidth	MHz	150	200	500	1000	1000	1000
Peak Power	kW	3000+	1000+	500	250	50	10
Average Power	w	6000+	1000+	500	250	50	10
Recovery Time ²	μs	5	3	2	<1	<1	<1
Loss – TR	dB	0.3	0.2	0.2	0.3	0.4	0.8
TRL		0.64	0.4	0.4	0.5	0.8	-
TRLL		0.84	0.6	0.6	0.8	1.4	-
Spike Leakage ³ –							
TR	ergs	1.0	0.30	0.25	0.25	0.25	0.15
TRL	Watts	2.0	5.0	5.0	5.0	5.0	-
TRLL	Watts	0.5	1.0	1.0	1.0	1.0	-
Phase Equality	Degrees	-	±3	±3	±3	±3	-
VSWR		1.3	1.3	1.3	1.3	1.3	1.3
Hard Braze		No	Yes	Yes	Yes	Yes	Yes
Quartz Pre TR		Yes	Yes	Yes	Yes	No	No
Passive TRL		Yes	Yes	Yes	Yes	Yes	No


NOTES:

1. Double power for dual TR, Triple power for single series mount.

2. 3 dB amplitude recovery.

3. TR spike leakage is traditionally measured in ergs.


4. Coaxial limiter.



MA-3252 (EIA-8835)

High Power Balanced ATR Duplexer

Bulletin 139



DESCRIPTION

The MA-3252 is a high power, balanced ATR Duplexer. This fixed tuned device was designed to operate over the 2.9 to 3.1 GHz frequency range and features liquid cooling and four ATR cells¹ which are field replaceable without disassembly of any waveguide connections.

APPLICATIONS

The MA-3252 is ideally suited for high power surveillance radar systems where highly reliable duplexing is required.

NOTE:

1. See Microwave Associates' Bulletin 140.




Microwave Associates , Inc. Burlington, Massachusetts Tel. (617) 272-3000

TWX: 710-332-6789 Telex: 94-9464

SPECIFICATIONS

Electrical Characteristics

Frequency Range Peak Power Average Power Pulse Width	2.9 to 3.1 GHz 3.0 mW, Max. 20.0 kW, Max. 30.0 μs	Isolation, Transmitter to Load: Transmit 26 dB, Min. Recovery Time 20 μs
Insertion Loss: Transmit Receive	0.15 dB, Max. 0.25 dB, Max.	Mechanical CharacteristicsSizeRefer to Outline DrawingWeight (Approx.)15 lbs.
Isolation, Transmitter to Receiver: Transmit Receive	26 dB, Min. 30 dB, Min.	Environmental CharacteristicsLife Test1000 hrs., Min.Temperature Range, Operating-54 to + 65° CAltitude10,000 Ft., Max.




All specifications are subject to change without notice.

3/73 Printed in U. S. A.

MA-3909X

X-Band Passive TR Limiter for Monopulse Radar

Bulletin 141



DESCRIPTION

The MA-3909X is a single channel, hardbrazed, phase controlled, passive TR Limiter designed to provide positive mixer diode protection in the 8.5 to 9.6 GHz frequency range.


APPLICATION

The MA-3909X is specifically designed to be used in conjunction with the dual TR Limiter MA-3910X in monopulse radars where long life, extended temperature range, and reliable receiver protector operation is required.

- Passive Operation: No ignitor bias or shutter required.
- Hardbrazed Construction: Performance independent of temperature.
- Mixer Diode Protection: Spike amplitude 5 watts maximum.
- Physical Configuration: 1.555 inch length fits most conventional TR sockets.



Min.	Typ.	Max.	Units
8.5		9.6	GHz
0		25	kW
0	—	25	W
-	_	5	μs
—	2	5	W
-	.04	.10	ergs
_	25	100	mW
-	50	100	mW
—	0.5	1.0	μs
_	0.7	1.0	dB
—	1.2	1.4	-
-5	-	+5	Degrees
2000	4000	-	Hours
ics			
-55	_	+71	°C
-55	-	+80	°C
	Dimensions	See Ou	Itline Drawing
Cadmium Plate, Iridite	Weight		10.0 oz
Aluminum, Iridite			(284 gr.
	8.5 0 0 - - - - - - - - 5 2000 ics -55 -55	8.5 - 0 - 0 - 0 - - 2 - .04 - 25 - .04 - 25 - .04 - 25 - 0.5 - 0.7 - 1.2 -5 - 2000 4000 ics -55 -55 - -55 - Cadmium Plate, Iridite Dimensions Weight Weight	n n




9/72 Printed in U.S.A.

MA-3910X

Dual X-Band Passive TR Limiter for Monopulse Radar

Bulletin 142



DESCRIPTION

The MA-3910X is a dual channel, hardbrazed, phase controlled, passive TR Limiter designed to provide positive mixer diode protection in the 8.5 to 9.6 GHz frequency range.


APPLICATION

The MA-3910X is specifically designed to be used in conjunction with the single TR Limiter MA-3909X in monopulse radars where long life, extended temperature range, and reliable receiver protector operation is required.

- Pre TR Input: High power handling with long life and fast recovery time.
- Passive Operation: No ignitor bias or shutter required.
- Hardbrazed Construction: Performance independent of temperature.
- Mixer Diode Protection: Spike amplitude 5 watts maximum.
- Physical Configuration: 1.555 inch length fits most conventional TR sockets.



SPECIFICATIONS				
Electrical Characteristics	Min.	Typ.	Max.	Units
Frequency Range	8.5	_	9.6	GHz
Peak Power	0	-	250	kW
Average Power	0	-	250	W
Pulse Width	—	-	5	μs
Arc Loss	-	0.4	0.6	dB
High Level VSWR	-	1.15	1.3	
Spike Leakage Amplitude	_	2	5	W
Spike Leakage Energy	-	.04	.10	ergs
Flat Leakage Power	_	50	100	mW
Breakdown Power	-	80	100	mW
Recovery Time, 3 dB	-	0.5	1.0	μs
Insertion Loss	_	0.7	1.0	dB
Low Level VSWR	_	1.15	1.30	
Phase Equality	-5	_	+5	Degrees
Life	2000	4000	_	Hours
Environmental Character	istics			
Operating Temperature	-55	_	+71	°C
Storage Temperature	-55		+80	°C
Mechanical Characteristic	xs			
Finish:	ish:		See	Outline Drawing
Input Flange	Cadmium Plate, Iridite	Dimensions Weight		16.0 oz
Output Flange	Aluminum, Iridite	0		(455 gr.
Body	Black Lacquer			



All specifications are subject to change without notice.

9/72 Printed in U.S.A.

MA-3949X

X-Band Passive TR Limiter for Airborne Radar

Bulletin 143



DESCRIPTION


The MA-3949X is a single channel, hardbrazed, passive TR Limiter designed to provide positive mixer diode protection in the 8.5 to 9.6 GHz frequency range.

APPLICATION

The MA-3949X is specifically designed to retrofit existing 1.070 inch conventional TR tube sockets in airborne and other radars where long life, extended temperature range, and reliable receiver protector operation is required.

FEATURES


- Passive Operation: No ignitor bias or shutter required.
- Hardbrazed Construction: Performance independent of temperature.
- Mixer Diode Protection: Spike amplitude 5 watts maximum.
- Physical Configuration: 1.070 inch length fits conventional TR sockets.



TWX: 710-332-6789 Telex: 94-9464


SPECIFICATIONS				
Electrical Characteristics	Min.	Typ.	Max.	Units
Frequency Range	8.5	-	9.6	GHz
Peak Power	0	-	10	kW
Average Power	0	-	10	W
Pulse Width	—	_	5	μs
Spike Leakage Amplitude	-	2	5	W
Spike Leakage Energy	_	.04	.10	ergs
Flat Leakage Power	_	25	50	mW
Breakdown Power	-	50	100	mW
Recovery Time, 3 dB	-	0.5	1.5	μs
Insertion Loss	-	0.5	0.8	dB
Low Level VSWR	-	1.2	1.4	-
Life	2000	4000	-	Hours
Environmental Character	istics			
Operating Temperature	-55	-	+85	°C
Storage Temperature	-55	-	+85	°C
Mechanical Characteristic	S			
Finish:		Dimensions	S	ee Outline Drawing
Input Flange	Cadmium Plate, Iridite	Weight		5.3 oz.
Output Flange	Aluminum, Iridite			(145 gr.)
Body	Black Lacquer			


OUTLINE DRAWING




DIMENSIONS

	Inc	hes	M.M.	
Dim.	Min.	Max.	Min.	Max.
A	1.060	1.080	26.92	27.43
В	1.610	1.640	40.89	41.66
С	1.276	1.284	32.41	32.61
D	1.216	1.224	30.89	31.09
E	-	1.228	-	31.19
F	-	.600	-	15.24
G	-	1.640	-	41.66








9/72 Printed in U.S.A.

MA-3940X

X-Band Passive TR Limiter for Tunnel Diode Amplifier or Low Noise Schottky Barrier Diode Protection

Bulletin 144



DESCRIPTION

The MA-3940X is a single channel, hardbrazed, passive TR Limiter designed to provide positive receiver protection in the 8.5 to 9.6 GHz frequency range.

APPLICATION

The MA-3940X is specifically designed with a two stage limiter to protect either tunnel diode amplifiers or low noise Schottky barrier diodes in radars where long life, extended temperature range, and reliable receiver protector operation is required.

FEATURES


- Passive Operation: No ignitor bias or shutter required.
- Hardbrazed Construction: Performance independent of temperature.
- Two Stage Limiter: Spike amplitude less than one watt.



Microwave Associates , Inc. Burlington, Massachusetts Tel. (617) 272-3000

Western Union Fax TWX: 710-332-6789 Telex: 94-9464

SPECIFICATIONS				
Electrical Characteristics	Min.	Тур.	Max.	Units
Frequency Range	8.5	_	9.6	GHz
Peak Power	0	_	30	kW
Average Power	0	_	30	W
Pulse Width	_	_	5	μs
Spike Leakage Amplitude	-	0.5	1.0	W
Spike Leakage Energy	_	.01	.02	ergs
Flat Leakage Power		10	20	mW
Breakdown Power		20	40	mW
Recovery Time, 3 dB	_	0.5	1.0	μs
Insertion Loss	_	0.8	1.0	dB
Low Level VSWR	—	1.3	1.5	_
Life	2000	4000	· · · · · · · · · · · · · · · · · · ·	Hours
Environmental Character	ristics			
Operating Temperature	-55	_	+71	°C
Storage Temperature	-55	_	+80	°C
Mechanical Characteristi	CS			
Finish:		Dimensions		See Outline Drawing
Input Flange	Cadmium Plate, Iridite	Weight		10.8 oz.
Output Flange	Aluminum, Iridite			(302 gr.)
Body	Black Lacquer	1		




All specifications are subject to change without notice.

^{9/72} Printed in U.S.A.

MA-3918X

X-Band Passive TR Limiter and STC Attenuator for Tunnel Diode Amplifier or Low Noise Schottky Barrier Diode Protection

Bulletin 145



DESCRIPTION

The MA-3918X is a single channel, hardbrazed, phase controlled, passive TR Limiter with integral, one step STC attenuator.

APPLICATION


The MA-3918X is specifically designed to allow external biasing of its two stage limiter to provide an additional 25 dB of attenuation for sensitivity time control. Two stages of limiting provide low leakage consistent with positive protection of tunnel diode amplifiers or low noise Schottky barrier diodes.

- STC Attenuation: 25 dB minimum attenuation with external bias.
- Passive Operation: No ignitor bias or shutter required.
- Hardbrazed Construction: Performance independent of temperature.
- Two Stage Limiter: Spike amplitude less than one watt.
- Pre TR Input: High power handling with long life and fast recovery time.




SPECIFICATIONS	ya watan yang u tina tan Andrea (Janetin Park) ya Kina Canaan na kan kan kan kan kan kan kan kan			
Electrical Characteristics	Min.	Typ.	Max.	Units
		175.	9.6	GHz
Frequency Range	8.5	-	9.0	kW
Peak Power	0		-	
Average Power	0	_	50	W
Pulse Width		_	5	μs
Spike Leakage Amplitude	—	0.5	1.0	W
Spike Leakage Energy		.01	.02	ergs
Flat Leakage Power	-	20	50	mW
Breakdown Power		25	50	mW
Recovery Time, 3 dB	-	0.5	0.8	μs
Insertion Loss	-	0.8	1.2	dB
Low Level VSWR	-	1.3	1.4	
Life	2000	4000	-	Hours
STC Attenuation	25	30	-	dB
STC Bias Current	30	50	_	mAdc
Environmental Characterist	ics			
Operating Temperature	-40	-	+70	°C
Storage Temperature	-55		+85	°C
Mechanical Characteristics				
Finish:		Dimensions		See Outline Drawing
Input Flange	Cadmium Plate, Iridite	Weight		11.5 oz.
Output Flange	Aluminum, Iridite			(324 gr.)
Body	Black Lacquer			





	Inc	hes	M.M.	
Dim.	Min.	Max.	Min.	Max.
A	2.358	2.366	59.89	60.10
в	1.610	1.640	40.89	41.66
С	1.276	1.284	32.41	32.61
D	1.216	1.224	30.89	31.09
E	.160	.170	4.06	4.32
F	.787	-	19.99	-
G	.192	.202	4.88	. 5.13
н	-	1.325	-	33.66
J	-	1.400	-	35.56
к	-	.900	-	22.86

DIMENSIONS



MA-3926Z

Dual Ku-Band Passive TR Limiter for Monopulse Radar

Bulletin 146



DESCRIPTION

The MA-3926Z is a dual channel, hardbrazed, phase controlled, passive TR Limiter designed to provide positive mixer diode protection in the 15.5 to 17.5 GHz frequency range.

APPLICATION


The MA-3926Z is specifically designed to be used in conjunction with the single TR Limiter MA-3927Z in monopulse radars where long life, extended temperature range, and reliable receiver protector operation is required.

- Passive Operation: No ignitor bias or shutter required.
- Hardbrazed Construction: Performance independent of temperature.
- Mixer Diode Protection: Spike amplitude 5 watts maximum.
- Physical Configuration: .807 inch length fits most conventional TR sockets.




SPECIFICATIONS				
Electrical Characteristics	Min.	Тур.	Max.	Units
Frequency Range	15.5	_	17.5	GHz
Peak Power	0	_	100	kW
Average Power	0	-	100	W
Pulse Width	-	-	3	μs
Spike Leakage Amplitude	-	1	2	W
Spike Leakage Energy	-	.02	.05	ergs
Flat Leakage Power	-	10	20	mW
Breakdown Power	-	50	100	mW
Recovery Time, 3 dB	-	0.5	1.0	μs
Insertion Loss	-	0.8	1.2	dB
Low Level VSWR	-	1.15	1.2	_
Life	2000	4000	-	Hours
Phase Equality	-5	-	+5	Degrees
Environmental Characteristics				
Operating Temperature	-40		+100	°C
Storage Temperature	-55	-	+100	°C
Mechanical Characteristics				
Finish:		Dimensions	See	Outline Drawing
	dmium Plate, Iridite	Weight		4.5 oz.
Output Flange	Aluminum, Iridite			(127 gr.)
Body	Black Lacquer			11 = 1 5


OUTLINE DRAWING




	Inc	hes	M.M.	
Dim.	Min.	Max.	Min.	Max.
A	.802	.812	20.37	20.62
В	1.292	1.332	32.82	33.83
С	.952	.960	24.18	24.38
D	.990	.998	25.15	25.35
E	1.297	1.812	32.94	46.02
F	.142	.149	3.61	3.78

DIMENSIONS








MA-3927Z

Ku-Band Passive TR Limiter for Monopulse Radars

Bulletin 147



DESCRIPTION

The MA-3927Z is a single channel, hardbrazed, phase controlled, passive TR Limiter designed to provide positive mixer diode protection in the 15.5 to 17.5 GHz frequency range.

APPLICATION

The MA-3927Z is specifically designed to be used in conjunction with the dual TR Limiter MA-3926Z in monopulse radars where long life, extended temperature range, and reliable receiver protector operation is required.

FEATURES

- Passive Operation: No ignitor bias or shutter required.
- Hardbrazed Construction: Performance independent of temperature.
- Mixer Diode Protection: Spike amplitude 5 watts maximum.
- Physical Configuration: .807 inch length fits most conventional TR sockets.



TWX: Microwave Associates, Inc. Burlington, Massachusetts Tel. (617) 272-3000


Western Union Fax TWX: 710-332-6789 Telex: 94-9464

SPECIFICATIONS				
Electrical Characteristics	Min.	Тур.	Max.	Units
Frequency Range	15.5	-	17.5	GHz
Peak Power	0	_	20	kW
Average Power	0	-	20	W
Pulse Width	_	—	3	μs
Spike Leakage Amplitude		2	5	W
Spike Leakage Energy	_	.04	.10	ergs
Flat Leakage Power	_	25	100	mW
Breakdown Power	_	50	100	mW
Recovery Time, 3 dB	-	0.5	1.0	μs
Insertion Loss	-	0.8	1.2	dB
Low Level VSWR	-	1.3	1.5	<u> </u>
Life	2000	4000	_	Hours
Phase Equality	-5	-	+5	Degrees
Environmental Character	istics			
Operating Temperature	-40	_	+100	°C
Storage Temperature	-55	_	+100	°C
Mechanical Characteristic	S			
Finish:		Dimensions	See C	Jutline Drawing
Input Flange	Cadmium Plate, Iridite	Weight		3.5 oz
Output Flange	Aluminum, Iridite			(98 gr.
Body	Black Lacquer			



	Inches		M.M.	
Dim.	Min.	Max.	Min.	Max.
A	.802	.812	20.37	20.62
В	1.297	1.327	32.94	33.71
С	1.735	1.765	44.07	44.83
D	.952	.960	24.18	24.38
E	1.495	1.505	37.97	38.23
F	1.297	1.812	32.94	46.02
G	.142	.149	3.61	3.78

DIMENSIONS




All specifications are subject to change without notice.

MA-31002X

X-Band Ferrite Diode Limiter

Bulletin 148



DESCRIPTION

Microwave Associates' new ferrite diode limiter (the MA-31002X) is an all solid-state, completely passive and superior performing device covering the 9.2 to 9.4 GHz frequency range. It is designed chiefly to provide receiver protection at all times -either from the transmitter or other external sources. This device eliminates the need for power supplies and shutters and, since it is absorptive, four-port circulators and dummy loads are not required in some systems utilizing the new "FDL".

APPLICATIONS

The MA-31002X is a boon to the system which requires high power, long life and reliability . . . together with a limited space factor.

- Extremely long lifetime
- Fast recovery time
- High power capabilities



SPECIFICATIONS

Electrical Characteristics

Frequency Range	9.2-9.4 GHz
Peak Power	80 kW
Average Power	80 W
Pulsewidth	5.0 μs
Spike Leakage Amplitude	0.5 W
Spike Leakage Energy	0.05 ergs
Flat Leakage Power	20 mW
Recovery Time, 3 dB	0.05 μs
Insertion Loss	1.0 dB
Low Level VSWR	1.3
Life	10,000 + Hours


Mechanical Characteristics


Insertion Length	5.50 Inches
Weight	32 oz.
Finish	
Flanges (Input and Output)	Aluminum Iridite
Body	Black Lacquer

Environmental Characteristics

Temperature	
Operating	-55 to
Storage	-55 to

OUTLINE DRAWING





H (4 HOLES)	
	G

+71°C +85°C

	LIMITS		
DIM.	MIN.	NOM.	MAX.
А	.060	_	_
В	_	_	1.875
С	-	_	.563
D	-	_	1.640
E	1.215	1.220	1.224
F	1.610	1.625	1.640
G	1.276	1.280	1.284
Н	#8-32 UNC-2B X .250 DP ¹		
J	.235	.250	.265
К	_	_	5.50 ^{±.01}
L	_	-	2.200

NOTE:


 The AQL for the combined mechanical defectives in quality conformance inspection shall be one per cent. MIL-STD-105 applies.

4/73 Printed in U.S.A.

MA-31003X

X-Band Ferrite Diode Limiter

Bulletin 149



DESCRIPTION


Microwave Associates' new ferrite diode limiter (the MA-31003X) is an all solid-state, completely passive and superior performing device covering the 9.0 to 9.6 GHz frequency range. Similar to its co-worker, the MA-31002X in the 9.2 to 9.4 GHz range, this device is designed chiefly to provide receiver protection with performance characteristics surpassing those of the gas or gas solid-state TR model.

APPLICATIONS

The MA-31003X is ideally suited for weather radar or other types of airborne environments where reliable receiver protection is required.

FEATURES

- Extremely long lifetime
- Fast recovery time
- High power capabilities
- Light weight
- Compact size



TWX: 710-332-6789 Telex: 94-9464

SPECIFICATIONS

Electrical Characteristics

Frequency Range	9.0-9.6 GHz
Peak Power	10 kW
Average Power	10 W
Pulsewidth	5 µs
Spike Leakage Amplitude	.5 W, Max.
Spike Leakage Energy	.05 ergs, Max.
Flat Leakage Power	20 mW, Max.
Breakdown Power	40 mW, Max.
Recovery Time, (3 dB)	.05 µs
Insertion Loss	1.0 dB
Low Level VSWR	1.4
Life	10,000 + Hours


Mechanical Characteristics

Insertion Length	2.750 ± .01 Inches
Weight	12.0 oz.
Finish	
Flanges (Input and Output)	Aluminum Iridite
Body	Black Lacquer

Environmental Characteristics

Temperature Operating Storage

-55 to +71°C -55 to +80° C



G


		LIMITS	
DIM.	MIN.	NOM.	MAX.
A	.060		_
В	-	-	1.875
С			.125
D		-	1.640
E	1.216	1.220	1.224
F	1.610	1.625	1.640
G	1.276	1.280	1.284
н	# 8-32 UNC-2B X .250 DP		
J	.235	.250	.265
к	2.740	2.750	2.760
L	_	-	2.200

NOTE:

1. The AQL for the combined mechanical defectives in quality conformance inspection shall be one per cent. MIL-STD-105 applies.

MA-31006Z Ku-Band Ferrite Diode Limiter

Bulletin 150



DESCRIPTION

The MA-31006Z ferrite diode limiter is an all solid-state, completely passive device covering the 16.0 to 17.0 GHz frequency range. Similar to the X-band models designed by Microwave Associates, this Ku-band unit is designed chiefly to provide superior receiver protection with performances surpassing those of the gas or gas solid-state TR models.

APPLICATIONS

This new Ku-band device is ideally suited for requirements demanding high reliability receiver protection.

FEATURES

- Fast recovery time
- Extremely long lifetime
- Light weight
- High reliability

Microwave Associates , Inc. Burlington, Massachusetts Tel. (617) 272-3000

TWX: 710-332-6789 Telex: 94-9464

SPECIFICATIONS


Electrical Characteristics

Frequency Range	16.0-17.0 GHz
Peak Power	4.0 kW
Average Power	4 W
Duty Cycle	0.001
Spike Leakage Amplitude	1.0 W
Flat Leakage Power	40 mW
Breakdown Power	40 mW
Recovery Time, (3 dB)	.05 µs
Insertion Loss	1.40 dB
VSWR	1.4:1
Life	10,000 + Hours

Mechanical Characteristics

Insertion Length	2.285 ± .01 Inches	
Weight	7.0 oz.	
Finish		
Flanges (Input and Output)	Aluminum Iridite	
Body	Black Lacquer	
Environmental Characteristics		
Temperature		
Operating	-55 to +71°C	
Storage	-55 to +85°C	


OUTLINE DRAWING



MA-31005S

S-Band Ferrite Diode Limiter

Bulletin 151A




DESCRIPTION

Microwave Associates' new ferrite diode limiter (the MA-31005S) is an all solid-state, completely passive, superior performance device covering the 2.9 to 3.1 GHz frequency range. It is designed to provide receiver protection at all times – either from the transmitter or from other external sources. This device eliminates the need for power supplies and shutters. Since it is absorptive, four-port circulators and dummy loads are not required in some systems utilizing the new "FDL" as part of the duplexer.

APPLICATIONS

The MA-31005S is a boon to systems which require high power protection, long life and reliability.

- Extremely long lifetime
- Fast recovery time
- High power capabilities
- Absorptive



SPECIFICATIONS Electrical Characteristics

Frequency Range	2.9 - 3.1 GHz
Peak Power	15 kW
Average Power	15 W
Pulsewidth	20 μs
Spike Leakage Amplitude	0.5 W
Spike Leakage Energy	0.05 ergs
Flat Leakage Power	40 mW
Recovery Time, 3 dB	0.5 μs
Insertion Loss	1.0 dB
Low Level VSWR	1.4
Life	10,000 Hours

Mechanical Characteristics


9.75 Inches
130 oz.
Aluminum Iridite
Black Lacquer

Environmental Characteristics

Temperature Operating

Storage

-40 to +70°C -55 to +85°C




	LIMITS			
DIM.	MIN.	NOM.	MAX.	
A	9.635	9.750	9.765	
В	2.835	2.850	2,865	
С	-	-	2.500	
D	2.980	3.000	3.020	
E	0.360	0.380	0.400	
F	.125	_	_	
G	-	-	4.500	
н	1.159	1.164	1.169	
J	0.576	0.578	0.580	
к	1.279	1.281	1.283	
L	1.912	1.914	1.916	
м	_	-	4.00	
N	¼ - 20 UNC-2B x .35 DP			
Р	_	-	0.50	
R	-	-	4.52	

MA-31008C

C-Band Ferrite Diode Limiter

Bulletin 152



DESCRIPTION

Microwave Associates' new ferrite diode limiter (the MA-31008C) is an all solid-state, completely passive, superior performance device covering the 5.5 to 5.9 GHz frequency range. It is designed to provide receiver protection at all times – either from the transmitter or from other external sources. This device eliminates the need for power supplies and shutters. Since it is absorptive, four-port circulators and dummy loads are not required in some systems utilizing the new "FDL" as part of the duplexer.

APPLICATIONS

The MA-31008C is a boon to systems which require high power protection, long life and reliability.

FEATURES

- Extremely long lifetime
- Fast recovery time
- High power capabilities
- Absorptive



TWX: 710-332-6789 Telex: 94-9464

SPECIFICATIONS

Electrical Characteristics

Frequency Range	5.4 - 5.9 GHz
Peak Power	15 kW
Average Power	15 W
Pulsewidth	5 µs
Spike Leakage Amplitude	0.5 W
Spike Leakage Energy	0.05 ergs
Flat Leakage Power	40 mW
Recovery Time, 3 dB	0.1 μs
Insertion Loss	0.8 dB
Low Level VSWR	1.4
Life	10,000 Hours

Mechanical Characteristics


Insertion Length	6.00 Inches
Weight	60 oz.
Finish	
Flanges (Input and Output)	Aluminum Iridite
Body	Black Lacquer

Environmental Characteristics

Temperature Operating Storage

-40 to +70°C -55 to +85°C

OUTLINE DRAWING



	LIMITS		
DIM.	MIN.	NOM.	MAX.
A	5.985	6.000	6.015
В	-	-	2.25
С	-	-	1.75
D	2.48	2.50	2.52
E	3.48	3.50	3.52
F	3.60	3.625	3.65
G	0.125	-	-
н	0.23	0.25	0.27
J	-	-	2.25
к	0.561	0.563	0.565
L	1.412	1.414	1.416
м	0.436	0.438	0.440
N	0.911	0.914	0.917
Р	3.245	3.250	3.255
Q	.221D (8) HOLES SPACED EQUALLY WITHIN .005 pf TRUE POSITION		
R	0.867	0.872	0.877
S	1.867	1.872	1.877
Т	%-20 UNC-2B .25 DEEP		
U	-	-	1.00

All specifications are subject to change without notice.



Microwave Associates, Inc. South Avenue Burlington, Mass. 01803 Tel. (617) 272-3000 TWX 710-332-6789 Western Union FAX TELEX 94-9464